

**Known Models:** All Walkie-Talkies w/plug-in crystals, old tube-type w/plug-in crystals.

**Synthesis:** None. These use direct conversion. The TX crystal is the direct on-channel frequency. The RX crystal is always 455 KHz lower, resulting in the only IF stage. You can replace these channels with any of the higher ones in the 40-channel CB band, or switch in extra crystals beyond the existing socket choices. This is exactly how all 3-Ch., 6-Ch., and 23-Ch. CB Walkie-Talkies and older tube CBs are set up.

Channel	TX Only	RX Only	Channel	TX Only	RX Only
Ch. 1 (26.965)	26.965	26.510	Ch.13 (27.115)	27.115	26.660
Ch. 2 (26.975)	26.975	26.520	Ch.14 (27.125)	27.125	26.670
Ch. 3 (26.985)	26.985	26.530	Ch.15 (27.135)	27.135	26.680
Ch. 4 (27.005)	27.005	26.550	Ch.16 (27.155)	27.155	26.700
Ch. 5 (27.015)	27.015	26.560	Ch.17 (27.165)	27.165	26.710
Ch. 6 (27.025)	27.025	26.570	Ch.18 (27.175)	27.175	26.720
Ch. 7 (27.035)	27.035	26.580	Ch.19 (27.185)	27.185	26.730
Ch. 8 (27.055)	27.055	26.600	Ch.20 (27.205)	27.205	26.850
Ch. 9 (27.065)	27.065	26.610	Ch.21 (27.215)	27.215	26.760
Ch.10 (27.075)	27.075	26.620	Ch.22 (27.225)	27.225	26.770
Ch.11 (27.085)	27.085	26.630	Ch.23 (27.255)	27.255	26.800
Ch.12 (27.105)	27.105	26.650			

*Compliments of:*

**CBC INTERNATIONAL · P.O. BOX 30655 · TUCSON AZ 85751 U.S.A.**

**TEL/FAX: 888-I-FIX-CBs (1-888-434-9227), (520) 298-7980 · Internet: [www.cbcintl.com](http://www.cbcintl.com) · Email: [info@cbcintl.com](mailto:info@cbcintl.com)**